

Work frequency	433.92 MHz ± 100KHz
Battery type	12 V VR22 alkaline
Intended use	Gate opener
This product conforms to directive 99/05/EEC	

### 1. MEMORY STORAGE OF A REMOTE CONTROL

- 1) Press the button on the receiver corresponding to the channel it is wished to memory store. The Led corresponding to the chose channel, will light up and stay on, indicating that the receiver is in learning mode.
- 2) Within 10 seconds, press the button on the remote control corresponding to the channel it is wished to memory store, and keep it pressed for at least 1 second.
- 3) If memory storage has successfully taken place, the Led flashes twice.
- 4) After memory storage of the first remote control, the receiver remains in learning mode, with the led continually lit.
- 5) To memory storage subsequent remote controls (up to a maximum of 256) repeat the procedure starting from point 2.
- 6) 10 seconds after memory storage of the last remote control, the receiver automatically leaves learning mode. It is possible to leave learning mode manually by pressing, once the remote control has been memory stored, one of the buttons on the receiver.

### 2. MEMORY STORAGE OF FURTHER REMOTE CONTROLS

It is possible to memory storage further remote controls by repeating the initial memory storage procedure or, without directly accessing the receiver, following this procedure:

- 1) Move close to the receiver and press buttons P1 and P2 on the already-memory stored remote control for at least 5 seconds.
- 2) Again, on the already-memory stored remote control, within 10 seconds press the button which is to be copied on the remote control to be added.
- 3) Press, on the remote control to be added, the button it is wished to memory store.
- 4) To add other remote controls, repeat the operations starting from point 3.

**Note: Wait at least 10 seconds after memory storage of the final remote control before pressing any further buttons.**

### 3. DELETION OF THE MEMORY

This procedure deletes all the remote controls memory stored on the receiver, from both channels. It is not possible to delete just one channel. Great care should be exercised in using this function.

To delete the memory of the receiver, you need to press, and keep pressed, one of the buttons on the receiver until the LEDs start to flash. Once flashing

has finished, the memory of the receiver has been completely deleted.

**Note: The receiver will not operate the gate until it has come out of learning mode.**

FR - XT4 433 RC (Code produit 787452-787454)

### DESCRIPTION ÉTIQUETTE ( Figure ② )

- A - Code d'identification du modèle
- B - Numéro d'identification du lot de production
- C - Lire les instructions
- D - Éliminer selon les directives en vigueur
- E - Référence organisme notifié (notified body)

Fréquence de fonctionnement	433.92 MHz ± 100KHz
Type batterie	12 V VR22 alcaline
Usage exclusif	Ouvre-portail
Ce produit est conforme à la directive 99/05/CEE	

### 1. MÉMORISATION DE LA TÉLÉCOMMANDE

- 1) Appuyer sur le bouton du récepteur relatif au canal qu'on souhaite mémoriser. Le LED correspondant au canal s'allumera fixe, signalant que le récepteur est en mode d'apprentissage.
- 2) Dans un délai de 10 secondes, appuyer sur la télécommande et maintenir enfoncée pendant 1 seconde au moins le bouton qu'on souhaite mémoriser.
- 3) Si la mémorisation est concluante, la LED exécute une paire de clignotements.
- 4) Après la mémorisation de la première télécommande, le récepteur reste en mode d'apprentissage et la LED est allumée fixe.
- 5) Pour mémoriser des télécommandes successives (jusqu'à un maximum de 256), répéter les opérations à partir du point 2.
- 6) 10 secondes après la mémorisation de la dernière télécommande, le récepteur sort automatiquement de la phase d'apprentissage. On peut sortir manuellement de la procédure d'apprentissage, une fois la télécommande mémorisée, en appuyant sur l'un des boutons du récepteur.

### 2. MÉMORISATION D'AUTRES TÉLÉCOMMANDES

On peut mémoriser d'autres télécommandes en répétant la procédure de programmation initiale ou, sans accéder directement au récepteur, en procédant comme suit:

- 1) S'approcher du récepteur, appuyer pendant 5 secondes au moins sur les boutons P1 et P2 de la télécommande déjà mémorisée.
- 2) Toujours sur la télécommande mémorisée, appuyer, dans un délai de 10 secondes, sur le bouton à copier sur la télécommande à ajouter.
- 3) Sur la télécommande à ajouter, appuyer sur le bouton qu'on souhaite mémoriser.
- 4) Pour ajouter d'autres télécommandes, répéter les opérations à partir du point 3.