

.. verified that I can see 192.168.1.100 via the remote station on AnyDesk!

(3)

.. setting up add of this Gateway to my DSE Webnet account
.. it shows "Active"

.. next steps

1) route ETH cable into control cabinet

3 documents all this

2) get trickle power running to system

.. start setting up templates in DSE Webnet

.. w/ key switch off connection drops; it reestablishes itself when key switches on.

.. turned Suricata firewall back on - seems OK

28 Feb 2025

.. after power is out to 890-04 module for 30 minutes the 7420 decides to enter Sleep Mode; pushing any button wakes it back up, but you can't do that remotely

.. need to download & install the DSE Configuration Suite

.. then under Miscellaneous Options can disable sleep mode and also set the Sleep timer

.. cust svc says:

1) go to Auto Mode & Sleep Mode will not happen

2) power 890 from 7420 terms 1 & 2 so that 890 will not lose power

3) can turn off Sleep Mode in Config Editor

.. I went to Auto Mode & now 7420 stays on even when 890 stops sending USB packets

.. Next, connected 890 power from DSE panel marked battery +12 on March 7. The DSE +12 is only energized when key switch is ON. Left wires from 12 VDC brick in place, but hanging not connected. This supply is not now plugged into the V10 VAC convenience outlet. System quickly & automatically reconnected to DSE Webnet.